

SBS-2 to driver to 30 Watt PA wiring diagram



A. Console 12 Volt input

B. Driver 12 Volt input

C. Driver 12 Volt output

D. Power amplifier 12 Volt input

E. Console left audio output

F. Console right audio output

G. Driver left audio input

H. Driver right audio input

I. Driver 1 Watt RF output

J. Power amplifier RF input

K. Power amplifier RF output

In order not to cause permanent damage to the power amplifier, always connect an antenna before powering up the transmitter.

Connect:

- Connector A to 12 Volt DC supply – 4 pin connector cable
- Connector B to 12 Volt DC supply – DC coaxial connector cable
- Connector C to connector D – DC coaxial to DC coaxial power cable
- Connector E to connector G – phono to phono audio cable
- Connector F to connector H – phono to phono audio cable
- Connector I to connector J – BNC to BNC RF cable
- Connector K to antenna cable – PL259 cable